

Bachelor of Engineering (Electrical Engineering), 4th Year 1st Sem. Exam, 2019(OLD)**SUBJECT : ELECTRIC UTILIZATION AND ILLUMINATION ENGG.** Page 1 of 2

Time: Three Hours

Full Marks: 100 (50 each part)

Use a separate Answer-Script for each part

Question No.	PART - I	Marks
1.	<p>Answer question no. 1 and any two from the rest Correct and/or justify the following statements (any six)</p> <p>(a) Power factor gets poorer due to distorted line current.</p> <p>(b) An LC tuned filter (for particular harmonics) offers capacitive effect at line frequency.</p> <p>(c) High voltage and low current is good for an arc furnace.</p> <p>(d) If the voltage is non-sinusoidal, the power contributed by the current harmonics is zero.</p> <p>(e) In direct arc furnace, any external means of stirring the charge is not required.</p> <p>(f) Any discharging rate does not necessarily give full Ampere-hour of a battery.</p> <p>(g) dT/dt charge termination method is employed for Li-ion batteries.</p>	6x3
2.(a)	<p>Why reactors must be used in an EAF?</p> <p>(b) Compare different types of electrodes used for arc furnace.</p> <p>(c) We got the following data from a 3 phase EAF. (Y-connected electrodes) Current drawn : 5kA Arc voltage : 50V Total resistance including electrode : 0.005Ω Total reactance including electrode : 0.02Ω Calculate the kVA and kW drawn from the supply, its p.f. and electrical efficiency.</p>	4+4+8

[Turn over

Use a separate Answer-Script for each part

Question No.	PART - I	Marks
3.(a)	Highlight different modes of battery charging.	8+5+3
	(b) Write down some merits of Li-ion batteries.	
	(c) What is Shedding in Lead acid batteries?	
4.(a)	Show how a non linear load injects harmonics into line current?	6+4+8
	(b) Show some applications of dielectric heating.	
	(c) Eight resistances each of 100 ohms are used in a resistance oven. If H is the maximum heat obtained from the oven, determine all possible heat output for a supply voltage of 220V, 50 Hz.	
5.	Write short notes on (any two)	8x2
	(a) Active shaping of line current.	
	(b) Choice of frequency for induction heating.	
	(c) Basic schemes of UPS	

BACHELOR OF ENGINEERING (ELECTRICAL ENGINEERING)
4th Year 1st Semester Examination, 2019 (OLD)
SUBJECT : ELECTRICAL UTILISATION & ILLUMINATION ENGINEERING

Time : Three hours

Full Marks -100
(50 marks for each part)

Use a separate Answer-Script for each part

Part II		Marks																											
Answer any three questions.																													
Two marks reserved for neatness and well organized answer.																													
1.a) b)	<p>Explain the terms: Illuminance, luminous intensity, luminance and polar plot.</p> <p>Estimate lumen output of a lamp from its SPD data:-</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>(λnm)</th> <th>< 400</th> <th>400-450</th> <th>450-500</th> <th>500-550</th> <th>550-600</th> <th>600-650</th> <th>650-700</th> <th>>700</th> </tr> </thead> <tbody> <tr> <td>\bar{V}_λ</td> <td>0</td> <td>0.008</td> <td>0.110</td> <td>0.780</td> <td>0.910</td> <td>0.320</td> <td>0.020</td> <td>0</td> </tr> <tr> <td>P_λ(W)</td> <td>1.5</td> <td>1.6</td> <td>1.8</td> <td>2.0</td> <td>2.3</td> <td>2.5</td> <td>3.1</td> <td>172.6</td> </tr> </tbody> </table>	(λ nm)	< 400	400-450	450-500	500-550	550-600	600-650	650-700	>700	\bar{V}_λ	0	0.008	0.110	0.780	0.910	0.320	0.020	0	P_λ (W)	1.5	1.6	1.8	2.0	2.3	2.5	3.1	172.6	16
(λ nm)	< 400	400-450	450-500	500-550	550-600	600-650	650-700	>700																					
\bar{V}_λ	0	0.008	0.110	0.780	0.910	0.320	0.020	0																					
P_λ (W)	1.5	1.6	1.8	2.0	2.3	2.5	3.1	172.6																					
2.a) b)	<p>Consider a room of dimensions 10m*8m*4m. The maintenance factor for the room is 0.8. Coefficient of Utilisation (COU) is 0.5. Find the number of luminaries (each luminaire having a luminous flux of 1000 lumens) required for obtaining an average illuminance of 150 lux on the working plane.</p> <p>Write short notes on Incandescent lamp, Compact fluorescent lamp and LED.</p>	16																											
3.a) b) c)	<p>Consider two light sources at a height of 10m from the working plane. The distance between the two light sources is 6m. The mean luminous intensities of the two light sources are 1000cd and 2000cd. Find the illuminance at the points just below the two light sources and at a point which is midway from the two light sources on the working plane.</p> <p>What are the functions of luminaires?</p> <p>State the laws of illumination.</p>	16																											
4.a) b)	<p>What are the functions of ballast in discharge lamps? Compare magnetic ballast with electronic ballast.</p> <p>A luminaire has an intensity distribution of $200(1+\cos\theta)$ and emits no light above. If the lamp emits 1000 lumens, find the Light Output Ratio of the luminaire using zonal lumen method.</p>	16																											
5. a) b) c) d) e)	<p>Write Short notes on the following (<u>any 4</u>):</p> <p>a) Simple Payback Analysis</p> <p>b) Luxmeter</p> <p>c) Distribution Photometer</p> <p>d) Integrating Sphere</p> <p>e) Halogen cycle in Tungsten Halogen Lamp</p>	16																											